

Quick Start

Powerline 1000

Model PL1000



NETGEAR®

Package Contents

In some regions, a resource CD is included with your product.




Get Started

Powerline adapters give you an alternative way to extend your network using your existing electrical wiring. Plug two or more Powerline adapters into electrical outlets to create a wired network connection. You can add up to eight Homeplug AV-certified and AV2-certified adapters to extend your network. For a complete list of Homeplug AV-certified devices, visit http://www.homeplug.org/certified_products.

Meet Your Adapter

Before you install your adapters, familiarize yourself with their LEDs, buttons, and ports.



Power LED



Solid green. The electrical power is on.

Solid amber. The adapter is in power saving mode.

Blinking green. The adapter is in the process of setting up security.

Off. The adapter is not receiving electrical power.

Ethernet LED



Solid green. The Ethernet port is linked.

Off. No Ethernet connection is detected.

Pick A Plug LED



The Pick A Plug feature lets you pick the electrical outlet with the strongest link performance, indicated by the color displayed by the LED:

Red. Link rate < 50 Mbps (good).

Amber. Link rate > 50 and < 80 Mbps (better).

Green. Link rate > 80 Mbps (best).

Off. The adapter did not find any other compatible Powerline devices using the same encryption key.

Factory Reset button

Press the **Factory Reset** button for one second, and then release it to return the Powerline adapter to its factory default settings.

Ethernet port

Use an Ethernet cable to connect your wired devices, including computers, WiFi routers, or game consoles, to your Powerline network.

Security button

Use the **Security** button to create a secure Powerline network.

➤ **To install your adapters:**

1. Plug in your new adapters.
2. Wait until the Pick A Plug LEDs are lit.

Congratulations. You installed your adapters and set up your network.


You can customize the network and security settings later.

Install Your Adapters

Do not plug your Powerline devices into extension cords, power strips, or surge protectors.

Room 1

Room 2



Do More

After your Powerline network is installed and running, you can expand your network, customize the network settings, and customize security.

Add Adapters

To add adapters before you configure the security feature, just plug them in and connect the adapters to your equipment.

➤ **To add an adapter to a Powerline network with security set:**

1. Plug the adapter into a wall outlet where you want to add Internet access.
2. If you used a private encryption key, press the **Security** button on one of the adapters that is already a part of the network for two seconds, and then press the **Security** button on the new adapter for two seconds.

Both buttons must be pressed within two minutes.

Note: The **Security** button does not work in power saving mode.

*Do not press the **Security** button on the Powerline adapter until installation is complete and the adapters are communicating with each other (indicated by the blinking Power LED). Pressing this button too*

soon can temporarily disable Powerline communication. If this occurs, use the **Factory Reset** button to return the Powerline adapter to its factory default settings.

Customize Your Network Security

When you first set up your network, the setup uses a default encryption key common to all Homeplug AV-certified adapters. You can change this.

➤ To create a private secure network:

1. Wait until the Pick A Plug LEDs are lit.
2. Press the **Security** button for two seconds on one adapter, and then press the **Security** button on one of the other adapters for two seconds. Both buttons must be pressed within two minutes.

Note: The **Security** button does not work in power saving mode (see *Troubleshooting Tips* on page 10).

Warning: Do not press the **Security** button on the Powerline adapter until installation is complete and the adapters are communicating with each other (indicated by the Power LED). Pressing this button too soon can temporarily disable Powerline communication. If this occurs, use the **Factory Reset** button to return the Powerline adapter to its factory default settings.

If you add adapters later, use this procedure to add the new adapters to your secure network.

Troubleshooting Tips

- Power LED is off. Make sure that power is supplied to the electrical outlet, and that the Powerline devices are not plugged into an extension cord, power strip, or surge protector.
- Power LED is amber. Power saving mode occurs when the Ethernet LED is off. This can occur in the following circumstances:
- The Ethernet cable is unplugged.
 - The device that is connected through the Ethernet cable is turned off.
 - The adapter is idle for 10 minutes. It returns to normal mode within two seconds after the Ethernet link is established.
- Pick A Plug LED is off.
 - If you already set network security, make sure that all Powerline devices are using the same encryption key; for information see the online user manual.
 - Press the **Factory Reset** button on each device for one second to return the Powerline adapter to its factory default settings.

Pick A Plug LED is
amber or red.

Something is interfering with communication between
adapters. To resolve this, do the following:

- Move the adapter to another outlet.
- Unplug devices that might be causing interference
such as surge suppressors and items with motors.

Ethernet LED is off.

- Make sure that the Ethernet cables are working
and securely plugged into the devices.
- Press the **Factory Reset** button on each device
for one second to return the Powerline adapter to
its factory default settings.

Support

Thank you for purchasing this NETGEAR product. You can visit www.netgear.com/support to register your product, get help, access the latest downloads and user manuals, and join our community. We recommend that you use only official NETGEAR support resources.

Trademarks

© NETGEAR, Inc., NETGEAR, and the NETGEAR Logo are trademarks of NETGEAR, Inc. Any non NETGEAR trademarks are used for reference purposes only.

Compliance

For the current EU Declaration of Conformity, visit http://support.netgear.com/app/answers/detail/a_id/11621/.

For regulatory compliance information, visit <http://www.netgear.com/about/regulatory/>.

See the regulatory compliance document before connecting the power supply.



201-19732-02

November 2015

NETGEAR, Inc.

350 East Plumeria Drive
San Jose, CA 95134, USA