

# NETGEAR® AirCard®

AT&T Unite Express™ (AC779S)

Data Sheet



## Slim, Sleek, and Shareable WiFi

Enjoy LTE connectivity on any WiFi enabled device with the touch of a button. The AirCard 779S mobile hotspot, also known as the AT&T Unite Express, is slim enough to slip into a bag or pocket, connects up to 10 WiFi devices, and lasts up to 10 hours on a single charge. With advanced built-in security options, you have full control over who shares your connection so that your data can stay protected no matter where you go.

## Key Features and Benefits

- 4G LTE with 3G fallback
- Powerful 2500 mAh battery that lasts up to 10 hours of continuous use
- 1.77" Color LCD display communicates network info, connectivity, battery life, and more
- Easy-to-use, just power-on and connect
- Secure with Guest WiFi, password protection, and the latest WiFi security protocols
- Connect up to 10 WiFi devices on-the-go without needing to search for public WiFi
- Slim and sleek profile makes it easy to pack for all kinds of travel
- Two TS-9 connectors available for optional 4G/3G antennas
- Conveniently manage your mobile hotspot from a tablet or smartphone by downloading our complimentary NETGEAR AirCard App

## Technical Specifications

### Technology / Bands

- 4G LTE:  
700 (B17) / 850 (B5) / 1700 (B4) / 1900 (B2) MHz
- 3G:  
850 (B5) / 1900 (B2) / 2100 (B1) MHz

### WiFi

- WiFi 802.11b/g/n
- Multiple SSID/Guest WiFi support
- WPS (WiFi Protected Setup) enabled

### Security

- WiFi security encryption
- WiFi Protected Setup (WPS)
- VPN pass-through
- NAT firewall
- Security web interface
- Multiple SSID/Guest WiFi support
- View & block connected devices from the touchscreen
- Password protected Web UI
- Ability to turn off WiFi or USB tethering

### Ports

- (2) TS-9 external 4G/3G antenna ports
- (1) microUSB port

### Battery

- Removable Li-ion battery (2500 mAh)
- Up to 10 hours of continuous usage

### Dimensions

- 112 mm (L) x 68 mm (W) x 15.3 mm (H)  
(4.41" x 2.67" x 0.6")

### Weight

- 80 g (2.8 oz) without battery
- 130 g (4.6 oz) with battery

### Environmental

- Operating temperature: 0 to 35° Celsius (32 to 95° Fahrenheit)
- Storage temperature: -40 to 85° Celsius (-40 to 185° Fahrenheit)
- RoHS compliant

### Antenna Diversity Support

- 2X2 MIMO (multiple-input and multiple-output) antenna for LTE

### SIM

- 3FF Format (microSIM)

### External Display

- 1.77" LCD display

### Package Contents

- NETGEAR AirCard® 779S Mobile Hotspot
- Pre-installed SIM card
- Removable Lithium Ion battery
- AC adapter
- Micro USB charging cable
- Quick start guide

# NETGEAR® AirCard®

AT&T Unite Express™ (AC779S)

Data Sheet

## Companion Products



**AirCard Signal Boosting Cradle with Ethernet**

Available on Amazon.com

[www.netgear.com/DC113A](http://www.netgear.com/DC113A)



**MIMO Antenna**

Available on Amazon.com

[www.netgear.com/ServiceProviders/AirCardAccessories](http://www.netgear.com/ServiceProviders/AirCardAccessories)



**NETGEAR AirCard App for mobile hotspots**

[www.netgear.com/AirCardApp](http://www.netgear.com/AirCardApp)

